

Designed in Japan

アイワ株式会社

AT-X80E II True Wireless Earphones

Unboxina

Microphone (

- AT-X80E II Earbuds
- Portable Charging Case

- User's Manual

Please refrain from using any damaged components; Contact your local authorized AIWA distributor/customer service.

Product Overview

button

Product Specifications

Model Number: AT-X80F II

BT Version: V51

Battery (Earbuds): 3.7V/38mAh

Battery (Charging Case): 3.7V/200mAh Supported Profiles: HEP/HSP/A2DP/AVRCP Sensitivity: 94dB ± 3dB S.P.L @ 1KHz

Transmission Distance (Estimated): 10 Meters (No. Obstacles)

Playback/Call Time: 4 Hours Standby Time: 70 Days Charging Time (Charging Case): 1.5 Hours

Charging Time (Earbuds): 1.5 Hours

The above are estimated values tested in a practical environment and may vary upon individual usage habits. Charging case holds approximately 2-3 charges of earbud's full battery capacity depending on playback volume.

Product Usage Guide

POWER ON:

(Automatic): Remove earbuds from charging case. (Manual): Press and hold both L and R side earbuds for

(Automatic): Place earbuds back into charging case.

(Manual): Press and hold both L and R side earbuds for

three (3) seconds SHUT DOWN:

USB charging port

- Micro-USB Charging Cable

- Silicone Ear-tips

five (5) seconds.

AUTOMATIC CONNECTION:

AT-X80E would automatically connect with the last

connected mobile device PLAY/PAUSE:

Click L or R side earbuds ONCE.

Press and hold L side earbud for two (2) seconds (Short

NEXT TRACK.

Press and hold R side earbud for two (2) seconds (Short "Beep"

VOLUME + : Double click L side earhud

PREVIOUS TRACK.

VOLUME -:

Double click R side earhud ANSWER/HANGUP CALLS: Click L or R side earbuds once.

DEJECT CALLS: Press and hold L or R side earbuds for two (2) seconds.

REDIAL NUMBER:

Triple Click L side earbud.

VOICE ASSISTANT:

Triple Click R side earbud.

LOW BATTERY PROMPT: Low battery notification tone will trigger every thirty (30) seconds until earbuds are powered off.

Charging

CHARGING THE CHARGING CASE.

Connect Micro-USB charging cable from a power converter/plug to the designated charging port on the charging case. Built-in LCD display will reflect the current battery

Connecting the Product LINK LEFT (L) AND RIGHT (R) SIDE EARBUDS

 Power on Earbuds (Automatically/Manually). 2. Earbuds will enter linking state (Alternating red &

white lights)

3. Earbuds will link automatically with each other (Sound prompt, One side indicator light will

extinguish, the other side will remain alternating red & white (either earbud) 4. Earbuds are now linked to each other and is ready to be paired with mobile device.

PAIR MOBILE DEVICE WITH FARBUDS

- 1. Turn on Bluetooth (BT) on your mobile device.
- Turn on Farbuds. 3. Search and connect to "AT-X80E" from your mobile

"Beep" prompt sound (R side) indicates successful Extinguished indicator lights on both earbuds

indicates successful pairing. SINGLE EARRUD PAIRING Please refer to the same pairing method (PAIR MOBILE DEVICE WITH

EARBUDS) as mentioned above.

level.

Place earbuds back into charging case to charge

CHARGING THE FARBUDS:

Earbuds indicator lights lighting up in red indicates charging in progress.

Earbuds indicator lights OFF indicates earbuds fully Built-in LCD will reflect current battery level of the

Built-in LCD will turn off upon earbuds full charge.

Precautions

1. Please charge device in a safe environment, Kindly avoid overcharging the device.

2. Please adjust the playback volume to an appropriate level to avoid hearing damage/loss of awareness to

vour surroundinas. 3. Avoid using earbuds in a place where there might

be interference signals. 4. Avoid using earbuds in a potentially dangerous situation/ harmful environment that might cause harm to the user/ product itself.



Aiwa Electronics Int'l Co., Ltd. Explore more at www.int-aiwa.com