

aiwa AIWA
Japan est.1951 Japan est.1951 Japan est.1951

AT-X80P
True Wireless Earphones

ENG
AIWA Electronics International Co., Ltd.
Explore more at www.int-aiwa.com

Product Schematic Picture

Wireless Headphones
charging case
Cotton - Linen Blend Fabric Pouch
Braided Nylon Type-C Charging Cable
Silicone Ear-Tips
User's manual

Product Specifications

Model: AT-X80P
BT Version: V5.1
IP Rating: IPX5
Rated voltage/current: 5V 1A
Rated Power: 3mW
Frequency Response: 20Hz-20KHz
Battery (Earbuds): 3.7V/30mAh
Battery (charging case): 3.7V/300mAh
Supported Profiles: A2DP, AVCTP, AVDTP, AVRCP, HFP, SPP, SMP, ATT, GAP, GATT, RFCOMM, SDP, L2CAP PROFILE
Audio Decoding: AAC, SBC Audio decodes
Impedance: 32Ω ±15%
Sensitivity: 104dB ±3dB
Transmission Distance (Estimated): 10 Meters (No Obstacles)
Working Time: 5 Hours (Approx)
Standby Time (Earbuds + Case): 280 Days (Approx)
Charging Time (Earbuds): 1.5 Hours (Approx.)
Charging Time (charging case with Earbuds): 2 Hours (Approx.)
Earbuds Weight: 3g each
Charging Case Weight: 32g

*Charging case holds approximately 2 full earbuds charges.

Schematic diagram of product operation

Touch Sensor
Power on/off
Indicator Light
Charging Contacts
Volume Up / Down
Pause / Play
Answer / Hang up a call
Game mode on/off
Type-C charging port
Charging case Indicator
Front of charging case
Rear of charging case

Product Instructions for Use

▶ Power ON:
Open the charging box cover and take the earphones out. The earphones will automatically turn on. Once turned on, the blue light on the earphones will remain illuminated for 2 seconds before entering pairing mode. The red and blue lights will then flash alternately during pairing. Upon successful pairing, the red and blue lights on the main earpiece will flash alternately, while the auxiliary earpiece will have no light effect.

Before using it for the first time, make sure the headset is fully charged.

▶ Power OFF:
Place the (left/right) earphone into the charging box separately, with the green light flashing once to check that the charging is normal. After closing the cover, the earphone will automatically turn off and begin to charge.

*AT-X80P will power OFF automatically after 3 minutes of disconnection.

▶ Music Control

Play / Pause Click touch sensor once (1)
Next Song Three click right touch sensor(3)
Previous Song Three click left touch sensor(3)
Volume + Double-click the right touch sensor(2)
Volume - Double-click the left touch sensor(2)

▶ Call Control

Answer/Hang up Click touch sensor once (1)
Reject Call Double-click the touch sensor (2)
Voice Assistant Long press the left touch sensor button for 2 seconds (2)
Game Mode on/off Long press the right touch sensor button for 2 seconds (2)

Connecting the Product

- Turn on Bluetooth (BT) on your mobile device.
- Remove the earphones from the charging case and connect to the "AIWA AT-X80P" from your Bluetooth device.
- The indicator light on the earbuds will turn off upon a successful connection.

Troubleshooting

L side earbud cannot be linked with R side earbud
Solution: Place the earbuds back into the charging case and close the case. Re-open the lid after a few seconds. The earbuds should now be linked to each other and are ready to be connected to your mobile device.

If the above solution does not work, please clear the earbuds' pairing history:

- Turn off and disconnect all Bluetooth devices from the earbuds.
- Remove ONE (1) earbud from the charging case and click on the touch sensor FOUR (4) times. The red light will flash three times.
- Place that earbud back into the charging case.
- Repeat this process for the other earbud.
- Remove both earbuds from the charging case and wait for them to link to each other before initiating pairing with your Bluetooth device

Battery & Charging

▶ Earbuds low battery
When the earphones have low battery, the red light flashes every 5 seconds and prompts with a 'Dong Dong' sound every 20 seconds. Please place the earphones in the charging box to recharge.

▶ Low battery of charging case
When the headphones are placed in the charging box or removed, the orange light on the charging box flashes 4 times, indicating that the charging box has low battery and needs to be charged. Please use a standard charger to charge it.

Place both earbuds back into the charging case.
*The charging case indicator light will turn solid green.
*Earbuds are fully charged when the charging case indicator light turns off.
*Approximate earbuds charging time: 1.5 hours.

While charging: Orange light flashes.
Full charge: Solid green light.
Unplug the charging cable: The charging box indicator light turns off.
Approximate charging case charging time: 1.5 hours.

aiwa AIWA
Japan est.1951 Japan est.1951 Japan est.1951

AIWA Electronics International Co., Ltd.
Explore more at www.int-aiwa.com

E-Manu

aiwa AIWA
Japan est.1951 Japan est.1951 Japan est.1951

คู่มือการใช้งาน

AT-X80P
True Wireless Earphones

THAI
AIWA Electronics International Co., Ltd.
Explore more at www.int-aiwa.com

ภาพรวม

หูฟังไร้สาย
เคสชาร์จ
ถุงผ้า
สายชาร์จ USB-Type C
ซิลิโคนหูฟัง
คู่มือการใช้งาน

ข้อมูลจำเพาะ

Model: AT-X80P
BT Version: V5.1
IP Rating: IPX5
Rated voltage/current: 5V 1A
Rated Power: 3mW
Frequency Response: 20Hz-20KHz
Battery (Earbuds): 3.7V/30mAh
Battery (charging case): 3.7V/300mAh
Supported Profiles: A2DP, AVCTP, AVDTP, AVRCP, HFP, SPP, SMP, ATT, GAP, GATT, RFCOMM, SDP, L2CAP PROFILE
Audio Decoding: AAC, SBC Audio decodes
Impedance: 32Ω ±15%
Sensitivity: 104dB ±3dB
Transmission Distance (Estimated): 10 Meters (No Obstacles)
Working Time: 5 Hours (Approx)
Standby Time (Earbuds + Case): 280 Days (Approx)
Charging Time (Earbuds): 1.5 Hours (Approx.)
Charging Time (charging case with Earbuds): 2 Hours (Approx.)
Earbuds Weight: 3g each
Charging Case Weight: 32g

เคสชาร์จสามารถชาร์จหูฟังได้เต็มประมาณ 2 ครั้ง

วิธีการใช้งาน

เซ็นเซอร์สัมผัส
เปิด / ปิด
ไฟแสดงสถานะ
ไมค์
ไฟแสดงสถานะการชาร์จ
เพิ่ม/ลดเสียง
หยุด/เล่นเพลง
รับสาย/วางสาย
เปิด/ปิด โหมดเกม
พอร์ตชาร์จ USB Type C
ไฟแสดงสถานะการชาร์จ
ด้านหน้าเคสชาร์จ
ด้านหลังเคสชาร์จ

วิธีการใช้งาน

▶ เปิดเครื่อง

- เมื่อเปิดเคสชาร์จ หูฟังจะเปิดโดยอัตโนมัติ
- ไฟสีฟ้าจะติดค้างเป็นเวลา 2 วินาที
- ไฟสีแดงและสีน้ำเงินจะกะพริบสลับกันระหว่างการจับคู่
- เมื่อจับคู่สำเร็จ ไฟสีแดงและสีน้ำเงินบนหูฟังหลักจะกะพริบสลับกัน ในขณะที่หูฟังเสริมจะไม่มีแสง

ก่อนที่จะใช้งานเป็นครั้งแรก ตรวจสอบให้แน่ใจว่าชุดหูฟังชาร์จเต็มแล้ว

▶ ปิดเครื่อง

- ใส่หูฟังกลับเข้าไปในเคสชาร์จ โดยไฟสีเขียวจะกะพริบหนึ่งครั้งเพื่อตรวจสอบว่าการชาร์จเป็นปกติ
- หลังจากปิดฝาครอบแล้ว หูฟังจะปิดโดยอัตโนมัติและเริ่มชาร์จ

AT-X80P จะปิดเครื่องโดยอัตโนมัติหลังจากขาดการเชื่อมต่อเป็นเวลา 3 นาที

▶ การเล่นเกม

- เล่น/หยุดชั่วคราว: กดเซ็นเซอร์สัมผัส หูฟัง 1 ครั้ง
- เพลงถัดไป: กดเซ็นเซอร์สัมผัส หูฟังด้านขวา 3 ครั้ง
- เพลงก่อนหน้า: กดเซ็นเซอร์สัมผัส หูฟังด้านซ้าย 3 ครั้ง
- ระดับเสียง +: กดเซ็นเซอร์สัมผัส หูฟังด้านขวา 2 ครั้ง
- ระดับเสียง -: กดเซ็นเซอร์สัมผัส หูฟังด้านซ้าย 2 ครั้ง

ควบคุมการโทร

รับสาย/วางสาย และเซ็นเซอร์สัมผัส 1 ครั้ง
ปฏิเสธสาย และเซ็นเซอร์สัมผัส 2 ครั้ง
Voice Assistant กดปุ่มเซ็นเซอร์สัมผัสด้านซ้ายค้างไว้เป็นเวลา 2 วินาที
เปิด/ปิดโหมดเกม กดปุ่มเซ็นเซอร์สัมผัสด้านขวาค้างไว้เป็นเวลา 2 วินาที

การเชื่อมต่ออุปกรณ์

- เปิดบลูทูธ (BT) บนอุปกรณ์มือถือของคุณ
- ถอดหูฟังออกจากเคสชาร์จ และเชื่อมต่อกับ Bluetooth "AIWA AT-X80P" จากอุปกรณ์บลูทูธของคุณ
- ไฟแสดงสถานะหูฟังจะดับลงเมื่อการเชื่อมต่อสำเร็จ

หูฟังไม่สามารถเชื่อมต่อกับอุปกรณ์ได้

หูฟังด้าน L (ซ้าย) ไม่สามารถเชื่อมต่อกับหูฟังด้าน R (ขวา) ได้
วิธีแก้ไข: ใส่หูฟังกลับเข้าไปในเคสชาร์จและปิดเคสชาร์จ เปิดฝาขึ้นอีกครั้ง หลังจากผ่านไป 2-3 วินาที ตอนนี้หูฟังจะเชื่อมต่อกันทั้งสองข้าง และจะเชื่อมต่อกับอุปกรณ์ของคุณ

หากวิธีการแก้ไขข้างต้นไม่ได้ผล โปรดลบประวัติการจับคู่หูฟังออกจากมือถือ

- ปิดและยกเลิกอุปกรณ์บลูทูธทั้งหมดออกจากมือถือและอุปกรณ์ที่เชื่อมต่อ
- ถอดหูฟังหนึ่งข้างออกจากกล่องชาร์จ และแตะที่เซ็นเซอร์สัมผัส 4 ครั้ง
- ใส่หูฟังกลับเข้าไปในเคสชาร์จ
- ทำขั้นตอนนี้ซ้ำกับหูฟังอีกข้าง
- ถอดหูฟังทั้งสองข้างออกจากเคสชาร์จ และรอหูฟังทั้งสองข้างเชื่อมต่อกันก่อนที่จะเริ่มจับคู่อุปกรณ์ของคุณ

แบตเตอรี่และการชาร์จ

▶ หูฟังแบตเตอรี่ต่ำ
ไฟสีแดงจะแสดง 'แบตเตอรี่ต่ำ' จะกะพริบอย่างรวดเร็วทุกๆ 5 วินาที และมีเสียงแจ้งเตือนทุกๆ 20 วินาที กรุณาใส่หูฟังลงในเคสชาร์จเพื่อชาร์จ

▶ เคสชาร์จแบตเตอรี่ต่ำ
เมื่อไฟแสดงสถานะแบตเตอรี่บนกล่องชาร์จกะพริบเป็นสีส้ม 4 ครั้ง แสดงว่ากล่องชาร์จมีแบตเตอรี่เหลือน้อยและจำเป็นต้องชาร์จ โปรดใช้เครื่องชาร์จมาตรฐานเพื่อชาร์จใหม่

ใส่หูฟังทั้งสองข้างกลับเข้าไปในเคสชาร์จ ไฟแสดงสถานะเคสชาร์จจะเปลี่ยนเป็นสีเขียวค้าง หูฟังจะชาร์จเต็ม เมื่อไฟแสดงสถานะเคสชาร์จดับลง ใช้เวลาประมาณ 1.5 ชั่วโมง ในการชาร์จหูฟังจนเต็ม

ขณะชาร์จ: ไฟสีเขียวกะพริบ
ชาร์จเต็ม: ไฟสีเขียวค้าง
ถอดปลั๊กสายชาร์จ: ไฟแสดงสถานะกล่องชาร์จดับลง
เวลาในการชาร์จกล่องชาร์จโดยประมาณ: 1.5 ชั่วโมง

aiwa AIWA
Japan est.1951 Japan est.1951 Japan est.1951

AIWA Electronics International Co., Ltd.
Explore more at www.int-aiwa.com

E-Manu